



Network all your analog audio gear easily and cost - effectively with Dante AVIO



Plug and play operation



Built for the road



Sample rates up to 96 kHz



16, 24, and 32 bit audio support



Excellent dynamic range, SNR and THD performance



Configurable gain/attenuation

Network Everything

Dante AVIO Analog Adapters let you use your favorite analog audio gear with any Dante-connected system, delivering the interoperability, performance and scalability that only networking can bring. Cost effective, compact and built for the road, Dante AVIO adapters bring the modern network connectivity that every audio pro needs in their toolbox.



Dante Audio over IP and ASE67 RTP transport formats



Power over Ethernet (PoE) support



Dante Domain Manager ready

Dante AVIO analog adapters are available as input or output versions in 1- or 2-channel configurations.

Plug & Play

Each Dante AVIO analog adapter is a complete, high performance Dante device, delivering all the automation and ease of use that have made Dante the most popular audio networking solution worldwide.

Dante AVIO analog adapters are automatically discovered and ready to use when connected, and no separate power supplies are required – just use a common PoE (Power over Ethernet) switch and Dante AVIO analog adapters are ready to go.



Built for the road

We've made Dante AVIO analog adapters road-ready and tour-tough. Sonically welded ABS enclosures and quality hardware are used throughout, while cable assemblies are stress-tested to ensure reliable operation under grueling conditions. Toss them in your toolbox, show after show.

All Dante

Dante AVIO adapters are all fully functional Dante interfaces, with all the features you'd expect from Dante audio networking. Each one delivers bit-perfect

audio reproduction, super-low latency and sample accurate synchronization across the entire network. All Dante devices automatically discover one another, and the entire system is managed by our easy-to-use Dante Controller software on any connected PC or Mac. Most importantly, every Dante device can connect to every other Dante device – no questions asked.

All Dante AVIO adapters are fully compatible with Dante Domain Manager (DDM) for IT-level security and management, while AES67 is supported for connection to non-Dante networks.

Cost-effective

We've worked hard to make the Dante AVIO family of products a cost-effective addition to any system or piece of gear, so that everyone can enjoy the benefits of Dante Audio networking has never been easier to or more affordable, no matter how you choose to use it.

Use cases

Analog Input

- Connect legacy mixers and consoles to a Dante network.
- Patch favorite DSPs, analog compressors and equalizers into a Dante system using a combination of Input and Output adapters.
- Connect stage DI boxes and keyboard instruments directly to a Dante network.
- Connect your wireless mic receiver to a Dante network.

Analog Output

- Connect analog powered speakers to your Dante audio network.
- Send audio to analog power amplifiers over a Dante audio network.
- Create easy drop-points for connecting cry rooms and overflow areas to a Dante network.
- Connect non-networked hearing aid loop amplifiers.
- Send audio from Dante network to analog in-ear monitor (IEM) transmitters

Specifications

Analog Input

Max signal level (balanced)
+24dBu / +4dBu / 0dBu 0dBV / -10dBV

Frequency Response
20Hz to 20kHz (-/+0.5dB)

Impedance
20k Ohm balanced
10k Ohm unbalanced

Dynamic Range: >100dB

Signal to Noise Ratio: >100

Total Harmonic Distortion: <0.01 at +4dBu

Connectors: RJ45 & XLR-F

Power: Class1 802.3af PoE

Power Consumption: <2 watts

Sample Rates: 44.1, 48, 88.2, 96 kHz

Bit depth: 16, 24, 32

Dante Device Latency
1, 2, or 5ms (configurable using Dante Controller)

Network Transport
Dante Audio over IP, AES67 RTP

Operating Temp: -10 to +50C

Storage Temp: -25 to +70C

Part Number
AVIO Analog in, 1 ch: Part# ADP-DAI-AU-1x0
AVIO Analog in, 2ch: Part# ADP-DAI-AU-2x0

Analog Output

Max signal level (balanced)
+18dBu / +4dBu / 0dBu 0dBV / -10dBV

Frequency Response
20Hz to 20kHz (-/+0.5dB)

Impedance
150k Ohm balanced
75k Ohm unbalanced

Dynamic Range : >100dB

Signal to Noise Ratio: >100

Total Harmonic Distortion: <0.01 at +4dBu

Connectors: RJ45 & XLR-M

Part Number
AVIO Analog out, 1 ch: Part# ADP-DAO-AU-0x1
AVIO Analog out, 2ch: Part# ADP-DAO-AU-0x2